

## WHAT IS CLAIMED IS:

1. A cable interface circuit comprising:
- an RF input for accepting RF signals as well as power ;
- an RF output;
- an RF tap;
- 5 a power tap; and
- an isolation circuit for connecting said power from said RF input to said power tap while preventing said power from being delivered to either said RF output or to said RF tap.
2. The cable interface circuit of claim 1 wherein said isolation circuit is constructed, at least in part, using co-planar wave guide techniques.
3. The cable interface circuit of claim 1 wherein said isolation circuit is operable for maintaining an insertion and return loss of said RF tap at less than 3.0dB at 5 MHZ.
4. The cable interface circuit of claim 1 wherein said isolation circuit further comprises:
- over voltage protection circuitry for protection against lightning surges.
5. The cable interface circuit of claim 1 wherein said over voltage protection circuitry includes safety caps.

6. The cable interface circuit of claim 4 wherein said over voltage protection circuit delivers any said over voltage to a surge protector external to said interface circuit.

7. The cable interface circuit of claim 4 wherein said isolation circuit and at least a portion of said over voltage protection circuit are constructed using co-planar wave guide techniques.

8. The cable interface circuit of claim 1 wherein said isolation circuit further comprising:  
over voltage protection circuitry for protection against voltages greater than 600 volts.

9. The cable interface circuit of claim 8 wherein said over voltage protection circuitry includes safety caps.

10. The cable interface circuit of claim 1 wherein said interface circuit further includes:  
cut-off circuitry for selectively receiving RF signals from said RF output.

11. The cable interface circuit of claim 10 wherein said cut-off circuitry is operable under control of signals received from said RF input.

12. The cable interface circuit of claim 10 wherein said cut-off circuitry includes relay contacts.

13. The cable interface circuit of claim 1 wherein said RF tap is bidirectional.

14. The cable interface circuit of claim 1 wherein said RF tap sends RF signals to an RF receiver contained within said interface circuit and receives RF signals for delivery to said RF input from an RF transmitter contained within said interface circuit.

15. The cable interface circuit of claim 14 wherein said RF receiver and said RF tuner include circuitry for communicating with a processor over bidirectional digital links.

16. The cable interface circuit of claim 15 wherein said processor is located remote from said interface circuit.

17. The cable interface circuit of claim 16 wherein said interface circuit further includes cut-off circuitry for selectively isolating said RF output from said RF input.

18. The cable interface circuit of claim 17 wherein said cut-off circuitry is operable under control of signals from said processor.

19. The cable interface circuit of claim 14 wherein said RF tap, said isolation circuit, said RF receiver, and RF transmitter are contained within a single housing.

20. The cable interface circuit of claim 19 wherein said housing includes a first non-rotational RF network connector connected to both said housing and to said RF input.

22. The cable interface circuit of claim 20 wherein said connector includes an outdoor F-connection for mating with said network connector.

23. A self-contained device for receiving signals from a coaxial cable and for delivering received ones of said signals to a tuner within said device, said device comprising:

an input for connection to said cable, said input including isolation circuitry for removing power from said cable and for delivery of said removed power for use in powering said device; said isolation circuitry also including circuitry for delivering lightning surge energy to a separate surge protection device; and said isolation circuitry also including circuitry for protection against voltages in excess of 600 volts.

24. The device of claim 23 wherein said isolation circuitry is constructed using co-planar wave guides.

25. The device of claim 24 wherein said isolation circuitry includes safety caps.

26. The device of claim 24 wherein said device includes an output for connection to a receiving device, said output operational for receiving signals from said input without significant attenuation.

27. The device of claim 26 wherein said co-planar wave guides are used to direct said signals.

28. The device of claim 27 wherein said tuner is bidirectional.

29. The device of claim 28 wherein signals from said bidirectional tuner are delivered to said cable via said input and not to said receiving device and wherein signals from said input are delivered to both said receiving device and to said tuner, at least in part, by said co-planar wave guides.

30. The device of claim 29 wherein said input signals and said output to said receiving device are RF signals.

31. The device of claim 30 wherein said tuner communicates with said input via bidirectional RF signals and wherein said device further includes a digital signal output for bidirectional communication with devices external to said device.

32. The device of claim 31 wherein said device includes an RF connector rotationally and electrically locked to said device, said connector having a relatively flat outer surface for mating with a network connector.

33. The device of claim 32 wherein said connector meets UL standard 1950 for electrical creepage and clearance.

34. An interface device for use as a front end to an RF processing circuit, said device comprising:

an input coaxial connector, said input connector having a center conductor and an outer shield;

5 an output coaxial connector, said output connector having a center conductor and an outer shield;

a housing for containing said device, said outer shields connected to said housing;

an inductance having one of its terminals connected to said input center conductor, and the other of its terminals connected to a second capacitor and also connected to a power bias tap;

a capacitance having one of its terminals connected to said input center conductor and the other of its terminals connected to the input of a directional coupler, said directional coupler having low insertion loss; and

said directional coupler having an output connected to said center conductor of said output coaxial connector, and having a connection to said RF processing circuit.

35. The interface device of claim 34 wherein said directional coupler is connected also to one terminal of a second capacitance and a second terminal of said second capacitance connected to said output center conductor.

36. The interface device of claim 35 wherein at least a portion of the connections between said input connector, said output connector, said first capacitor, said inductance and said directional coupler is constructed using co-planar wave guides.

37. The interface device of claim 35 wherein said capacitors are safety caps.

38. The interface device of claim 36 wherein said housing also includes therein an RF transmitter for transmitting RF signals to said input coaxial cable via said directional coupler, said directional coupler operational for preventing transmitted ones of said RF signals from said RF transmitter from going to said output coaxial connector.

39. The interface device of claim 38 wherein said housing includes a digital connector for delivering digital signals to said RF transmitter and for receiving digital signals from said RF receiver.

049581-P026US-10025288



40. A method for receiving RF signals from a coaxial cable and for delivering digital representations of received ones of said signals to digital output, said method comprising the steps of:

receiving RF signals from said cable at an RF input;

5 removing any AC line power received from said cable;

delivering any said removed power for use in powering said method;

removing any lightning surge energy received from said cable and delivery said removed surge energy to a separate surge protection device; and

removing any voltage in excess of 600 volts from any said received signals.

41. The method of claim 40 wherein said above-identified steps include using co-planar wave guides to transport at least a portion of said received signals.

42. The method of claim 41 wherein said removing step includes using safety caps.

43. The method of claim 41 further including the step of delivery to an RF output received ones of said RF signals from said input without significant attenuation, and without any power or lightning surges present at said RF output from said input.

44. The method of claim 43 wherein said co-planar wave guides are used to deliver said RF signals to said RF output.

45. The method of claim 44 wherein input RF signals are delivered to a bidirectional tuner and wherein signals from said bidirectional tuner are delivered to said RF input and not to said RF output and wherein RF signals from said RF input are delivered to both said RF output and to said tuner, at least in part, by said co-planar wave guides.

46. The method of claim 45 wherein said method is practiced entirely within a self-contained device.

47. The method of claim 45 wherein said bidirectional tuner communicates with devices external to said self-contained device via a bidirectional digital link.

for review only

48. A cable interface circuit comprising:

an RF input for accepting RF signals as well as power ;

an RF output;

an RF tap;

a power tap; and

means for connecting said power from said RF input to said power tap while preventing said power from being delivered to either said RF output or to said RF tap.

49. The cable interface circuit of claim 48 wherein said connecting means is constructed, at least in part, using co-planar wave guide techniques.

50. The cable interface circuit of claim 48 wherein said connecting means is operable for maintaining an insertion and return loss of said RF tap at less than 3.0dB at 5 MHZ.

51. The cable interface circuit of claim 48 wherein said RF tap sends RF signals to an RF receiver contained within said interface circuit and receives RF signals for delivery to said RF input from an RF transmitter contained within said interface circuit.

52. The cable interface circuit of claim 51 wherein said RF receiver and said RF tuner include means for communicating with a processor over bidirectional digital links.

53. The cable interface circuit of claim 52 wherein said interface circuit further includes means for selectively isolating said RF output from said RF input.

54. The cable interface circuit of claim 53 wherein said isolating means is operable under control of signals from said processor.

	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---